



MULTI-PARAMETER ANALYZER BJI1I1 (BMET-1108)

MULTI-PARAMETER ANALYZER BJ1111

MULTIMETER

Multi-parameter Analyzer simultaneously measures Ion, Conductivity, Dissolved Oxygen, Temperature that otherwise requires four different meters. With the appropriate probes installed, it can also simultaneously measure several or one parameters.



SPECIFICATIONS

Model	BJ1111
Old Model	BMET-1108
DC Voltage	$\pm (0.7\% + 2)$
- 60 mV / 600 mV / 6 V / 60 V / 600 V / 1000 V	$\pm (0.7\% + 2)$
AC Voltage	
- 60 mV / 600 mV / 6 V / 60 V / 600 V / 750 V	$\pm (0.8\% + 3)$
DC Current	
- 600 μ A / 6000 μ A / 60 mA / 600 mA	$\pm (1.2\% + 3)$
- 6 A / 10 A	$\pm (2.0\% + 10)$
AC Current	
Resistance	
- 600 Ω / 6 k Ω / 60 k Ω / 600 k Ω / 6 M Ω / 60 M Ω	$\pm (1.2\% + 5)$
Capacitance	
- 10 nF / 100 nF / 1000 nF / 10 μ F / 100 μ F / 1000 μ F / 10 mF	$\pm (3.0\% + 3)$
Frequency	
- 10 Hz / 100 Hz / 1000 Hz / 10 kHz / 100 kHz / 1000 kHz / 10 MHz	$\pm (1.0\% + 5)$
Display	6000 Counts
Auto / Manual Range	Yes
Bargraph Display	Yes
Relative Measurement	Yes
True RMS	Yes
MAX / MIN	Yes
Interface	USB interface
Data Hold	Yes
Diode Test	Yes
Transistor Test	Yes
Continuity	Yes
Back Light	Yes
Power Supply	4 x 1.5 V AA Batteries

Weight	Approx. 352.5 g / 360.5 g
Size	194 x 93 x 55 mm
Safety Standard / Rating	EN61010-1, EN61010-2-033, EN61326, CAT III 1000 V
Alt Name	Multimeter



Biolab Scientific Ltd.

Trillium Executive Center, East Tower, 675 Cochrane Dr, Markham, Ontario L3R 0B8, Canada
Email: info@biolabscientific.com | Website: www.biolabscientific.com